

# FST-951-ISO Series Intelligent Addressable Heat Detectors

The NOTIFIER® FST-951-ISO intelligent thermal detectors are designed for both performance and aesthetics. A new modern, sleek, contemporary design and advanced thermal technologies make the FST-951-ISO Series ideal for both system operation and building design. The point ID address, set using rotary decimal switches, provide specific detector locations.

The series includes a 135°F (57°C) fixed-temperature and rate-of-rise detectors. These thermal detectors provide effective, intelligent property protection in a variety of applications. These detectors are available in FlashScan® only. This series also includes positive (+) side isolation on the Signaling Line Circuit (SLC) and must be used in conjunction with an isolation base.

## Features

### **SLC LOOP:**

- Two-wire SLC loop connection
- Unit uses base for wiring
- Compatible with only FlashScan® protocol systems
- Built-in-Isolator Detector

### **ADDRESSING:**

- Addressable by device
- Rotary, decimal addressing  
(Refer to the NOTIFIER panel manuals for device capacity.)

### **ARCHITECTURE:**

- Designed to meet UL 521 7th Edition
- Sleek, low-profile, stylish design
- State-of-the-art thermistor technology for fast response
- Integral communications and built-in device-type identification
- Built-in tamper resistant feature
- Built-in functional test switch activated by external magnet

### **OPERATION:**

- Fixed temperature model (FST-951-ISO) factory preset to 135°F (57°C)
- Rate-of-rise model (FST-951R-ISO), 15°F (8.3°C) per minute
- 360°-field viewing angle of the two visual alarm indicators, LEDs blink green in Normal condition and turn on steady red in Alarm

### **MECHANICALS:**

- Sealed against back pressure
- SEMS screws for wiring of the separate base
- Designed for direct-surface or electrical-box mounting
- Plugs into separate base for ease of installation and maintenance

### **OTHER SYSTEM FEATURES:**

- Remote test feature from the panel
- Walk test with address display
- Low standby current

### **OPTIONS:**

- Remote LED output connection to optional RA100Z remote LED annunciation



## Installation

FST-951-ISO Series plug-in intelligent thermal detectors use a detachable base to simplify installation, service and maintenance. Installation instructions are shipped with each detector.

Mount detector base (all base types) on an electrical backbox which is at least 1.5" (3.81 cm) deep. For a chart of compatible junction boxes, see 'DN-60054'.

**NOTE:** Because of the inherent supervision provided by the SLC loop, end-of-line resistors are not required. Wiring "T-taps" or branches are permitted for Class "B" wiring only.

## Construction

These detectors are constructed of fire-resistant plastic. The FST-951-ISO Series plug-in intelligent thermal detectors are designed to commercial standards and offer an attractive appearance.

## Operation

Each FST-951-ISO Series detector uses one of the panel's addresses (total limit is panel dependent) on the NOTIFIER Signaling Line Circuit (SLC). It responds to regular polls from the control panel and reports its type and the status. If it receives a test command from the panel (or a local magnet test), it stimulates its electronics and reports an alarm. It blinks its LEDs when polled and turns the LEDs on when commanded by the panel. The FST-951-ISO Series offers features and performance that represent the latest in thermal detector technology.

## Product Line Information

**FST-951-ISO:** White, low-profile intelligent 135°F (57°C) fixed thermal sensor with positive (+) side BUILT-IN-ISOLATOR on the Signaling Line Circuit (SLC), FlashScan only

**FST-951R-ISO:** White, low-profile intelligent rate-of-rise thermal sensor with positive (+) side BUILT-IN-ISOLATOR on the Signaling Line Circuit (SLC), FlashScan only

### INTELLIGENT BASES

**B300-4-IS:** White, 4" base, standard flanged low-profile isolator mounting base

### MOUNTING KITS AND ACCESSORIES

**RA100Z(A):** Remote LED annunciation. 3-32 VDC. For use with B300-4-IS.

**M02-04-00:** Test magnet

**M02-09-00:** Test magnet with telescoping handle

### Specifications

**Size:** 2.0" (51mm) high; base determines diameter

– **B300-4-IS series:** 4" (10.2 cm) diameter

**Shipping weight:** 3.4 oz. (95 g)

**Operating temperature range:**

• FST-951-ISO, FST-951R-ISO Series: -4°F to 100°F (-20°C to 38°C)

**Detector Spacing:** UL approved for 50 ft. (15.24 m) center-to-center, FM approved for 25 x 25 ft. (7.62 x 7.62 m) spacing

**Relative humidity:** 10% – 93% non-condensing

**Thermal ratings:** Fixed-temperature set point 135°F (57°C), rate-of-rise detection 15°F (8.3°C) per minute

### ELECTRICAL SPECIFICATIONS

**Voltage range:** 15 - 32 volts DC peak

**Standby current (max. avg.):** 200µA @ 24 VDC (one communication every 5 seconds with LED enabled)

**Max current:** 4.5 mA @ 24 VDC ("ON")

## Listings and Approvals

Listings and approvals below apply to the FST-951-ISO Series detectors. In some cases, certain modules may not be listed by certain approval agencies, or listing may be in process. Consult factory for latest listing status.

- UL Listing: S747
- FM Approved

## Safety Instructions as per WEEE Standards



This product complies with the Waste Electrical and Electronic Equipment (WEEE) Directive 2002/ 96/ EC.

Components or assemblies bearing this or similar symbols shall not be treated as household or municipal waste. Waste electrical products (end of life) shall be recovered and disposed of at specialist WEEE disposal facilities.

Please contact your local authority, your distributor, or the manufacturer if you require more information about recycling WEEE.



This document is not intended to be used for installation purposes.  
We try to keep our product information up-to-date and accurate.  
We cannot cover all specific applications or anticipate all requirements.  
All specifications are subject to change without notice.

FlashScan®, NOTIFIER®, and System Sensor® are registered trademarks of Honeywell International, Inc.

©2025 by Honeywell International Inc. All rights reserved. Unauthorized use of this document is strictly prohibited.



### Honeywell Building Automation India

Unitech Trade Center, Sector-43, Block C,  
Sushant Lok Phase – I, Gurgaon – 122002

#### For more information

Tel: 0008000502167

[www.honeywellbuildings.in](http://www.honeywellbuildings.in)

Country of Origin: India