

# HN-S600P MIXER AMPLIFIERS

- 3 microphones and 2 auxiliary inputs
- 1 line out
- 100V,70V and 4-16 Ohms transformer-isolated speaker outputs
- Automatic mute function for paging and announcements
- Individual input gain controls with master volume control
- Bass and treble tone controls
- LED level meter
- Speaker output short circuit protection



## PRODUCT DESCRIPTION

Highly flexible mixer amplifiers are designed for a wide variety of voice and background music applications such as retail shops, restaurants and bars, service centers, houses of worship, warehouses etc.

Technical Specification	
Rated Power Output	260 W
Output Regulation	<3dB (no load to full load)
Speaker Output	19Ω (70V) 39Ω (100V) Low impedance: 4-16Ω
Input	MIC 1,2,3 600Ω, 5-8mV, unbalanced phone jack; AUX 1,2: 10kΩ, 300mV, unbalanced, RCA jack
Output	600Ω 1.2V
Frequency response	60-15000KHz, +/-3dB
THD	<0.5% at 1kHz (1/3 Rated output)
S/N ratio	>72dB
Tone Controls	BASS: 100Hz (+/- 10 dB), TREBLE: 12kHz (+/- 10dB)
Controls	5 input gain, 1 treble, 1 bass, 1 mute and power switch

Cooling	Internal 12 VDC fan, extensive heat sinking
Indicators	Power indicator LED, LED output level meter 0,2,4,6,8,10dB
Protection	AC Fuse: 8A Current limiter, short circuit and thermal protection circuits
Power Consumption	350W
AC Power Supply	220V, 50/60Hz
Dimensions	89(H)×483(W)×366(D)mm
Built-in Dimensions	2 U rack 19 inch
Carton Dimensions	185(H)×520(W)×435(D)mm
Net weight	13.68kg
Gross weight	15.32kg
Color	Panel: steel plate, black Case: steel plate, black

### For more information,

<https://honeywellbuildings.in>

Call: 1-800-103-0339

Email: [HBT-Indiabuildings@honeywell.com](mailto:HBT-Indiabuildings@honeywell.com)

### Honeywell HBT India Buildings

Unitech Trade Center, 5th Floor, Sector-43,

Block C, Sushant Lok Phase - I,

Gurgaon - 122002